CONTI :: maxx lavatory faucet M10

maxx lavatory faucet M10, with IR sensor, with temperature-mixing, chromed Touchless, electronically controlled lavatory faucet: Modular single-piece design without separate installation box, sturdy metal housing, chromed Integrated battery (maintenance via service cover) Infrared sensors with automatic setting feature, microprocessor Reliable solenoid valve ROBUST (minimal level of water pressure surge) and economic aerator Hot and cold water supply connection with flexible high-pressure hoses Check valves and built-in filters Temperature adjustable or fixable (vandal-resistant construction) Adjustable hot water limitation (mechanically) Temporary-off (cleaning) and continuous water flow time (filling of basin) adjustable with Touch Continuous-on and hygienic flush time adjustable with Touch Follow-up time, sensor-sensitivity adjustable with Touch 12, 24 or 48-hour hygienic flush adjustable with Touch Installation similar to conventional single-lever faucet Compatible with CNX and Service APP: Control of stored operational data, settings and control functions 6 V Lithium CRP2 - commercial; life time up to 4 years Battery: Mains supply: Plug-in transformer 110-240 V 50-60 Hz / 6 V VARIOconnect: For single and multiple power supply and data connection (Connection CNX and Service APP - see accessories) Operating pressure: 0,3-10 bar 6 l/ min 1,6 gpm (3 bar) Flow rate (approx.): Water temperature (max.): 80 °C Aerator: Economic aerator, CASCADE (self-cleaning) Flexible hoses: 350 mm Angle valve connection: G 3/8 143-Built-in filters: 0,5 mm mesh size 131 max.45 Sensor sensitivity: Automatic self-adapting sensor technology 103 Follow-up time: 1 s pre-set (adjustable with Touch 0-10 s) Continuous water flow 120 Ø33.5 **-**∕Ø54 and hygienic flush time: 2 min pre-set (adjustable with Touch 0,5-20 min) 350 Temporary-off: 2 min (fixed) DIN EN 200; €€ Engineering standards: 103 G3/8' Note: When integrated into the CNX Water Management System, the CNX Converter 6 V must be ordered separately. 72 When using the Service APP, the BLE Converter must be ordered separately. Only possible with mains and VARIOconnect versions. Battery Without Chrome 131.000.11 Mains ¢ (\cdot) Without Chrome 131.010.11 operation VARIOconnect \sim Without 131.016.11 Chrome